



E26 LED only  
2\*E26 Max 25W  
Not included

# Flush Mount Instruction

## Safety Warning

Turn off power at the breaker panel before starting installation.

---

## Installation Steps

### • Step 1: Attach Mounting Bracket

Secure the metal mounting bracket to the ceiling junction box using the supplied machine screws. Make sure the two tapped studs (or mounting screws) on the bracket point downward and are aligned parallel to each other.

### • Step 2: Wire Connections

1. Strip  $\approx$  1/2 in. of insulation from fixture wires if needed.
2. Hot: Connect the fixture's black wire to the black (hot) house wire.
3. Neutral: Connect the fixture's white wire to the white (neutral) house wire.
4. Ground: Connect the fixture's green/ground wire to the bare copper/green house ground.
5. Twist each pair together and secure with wire nuts, then gently tuck all connections into the box.

### • Step 3: Install Light Bulbs

Screw two E26 medium-base bulbs (max wattage per socket per fixture label) clockwise into the sockets until snug.

### • Step 4: Mount the Shade / Fixture Body

Lift the drum (or glass/metal shade) over the sockets, aligning its key-hole slots or mounting holes with the two studs protruding from the bracket. Slide the shade upward until it sits flush against the ceiling.

### • Step 5: Secure & Finish

Thread the decorative caps or knurled nuts onto the exposed studs and hand-tighten to lock the shade in place. Do not overtighten.

---

## Final Check

Restore power at the breaker panel and test the fixture. The flush mount should sit level, the bulbs should illuminate, and no wires should be visible.