

## INSTRUCTIONS

Read instructions carefully & save for future reference.

### PARTS

- (1) Angel & Stacked Stone Fountain
- (1) Angel Wings
- (1) Pump with 5m Cable
- (1) LED Light with 5m Cable (in fountain)
- (1) Solar Panel, Bracket, Tube, Spike

Ensure all parts are accounted for before disposing of packaging.


### FOUNTAIN ASSEMBLY

Select a level location to place the fountain. Assemble components on a smooth, clean surface to avoid scratching or damaging the finish.

1. Attach the angel wings to the back of the angel.



2. Attach the pump to the hose from the access panel on the back of the fountain body. The LED light is preassembled into the fountain reservoir. The pump and LED light cables should exit out from the access hole, ready for connection to the solar panel.




3. Fill the reservoir with water, ensuring the pump is completely submersed.





### SOLAR PANEL ASSEMBLY


4. Connect the bracket, tube and spike and attach the solar panel to the bracket as shown.



5. Insert the spike into the ground. Position the solar panel to face south (in northern hemisphere) to make the most of daylight hours. It is important to angle the solar panel towards the sun when sun is at its highest point. Ensure the solar panel is not shaded by trees, shrubs or buildings.



6. Connect the pump and LED light cables to the solar panel (charger sold separately).



7. Your new fountain is ready to use.



Over time, the fountain finish may gradually mellow in color, this is part of the natural aging process.

## 8. SOLAR PANEL OPERATION

**NOTE:** The LED light is designed to only work at nighttime.

**Continual ON Mode:** Press [Power on/off] button, the top indicator light [continual on] will be lit — the pump will run continuously until the battery power runs out. The pump will automatically restart when the solar panel battery has been sufficiently charged with sunlight.

**4-Hour Timer Mode:** Press [Timer modes] button until the second indicator light [4hrs Timer] is lit — the pump will run for 4 hours and stop. The pump will not run again until the solar panel is manually restarted.

**Daily 4-Hour Timer Mode:** Press [Timer modes] button until the third indicator light [daily 4hrs Timer] is lit — the pump will run for 4 hours and shut down (in standby) for 20 hours; this operation will repeat daily at the same time. You can reset the pump's daily start up time by switching it on at a new desired time in this same mode. **NOTE:** The third indicator light will blink slowly when the pump has reached the 4-hour runtime and be in standby for the following 20 hours. In order to save battery power, the indicator light will turn off but you can activate the indicator light to check its status with a single push of either button, the indicator light will be on for a while and shut off again.

### BATTERY LOW [RED INDICATOR LIGHT BLINKING]:

Battery power is low and the pump will stop running soon for protecting the battery. The red indicator light will turn off after the solar panel receives enough sunlight for the battery to be recharged.


**PLEASE NOTE:** This model allows for the battery pack to be charged with an original electric charger (sold separately). Only use the original battery charger as alternatives may damage the battery and will void the warranty. See contact information under WARRANTY to order the compatible charger.

## 9. PERFORMANCE OF PUMP

The performance of the pump depends on the orientation of the solar panel being toward the sun and sunlight strength; pump performance is not guaranteed when the solar panel is in the shade or poor weather conditions. Max. Data is obtained during optimal conditions; solar panel performance cannot be guaranteed if placed in the shade or during poor weather conditions. The performance of the pump also depends on the battery power level, the pump cannot operate if battery power is low.

## 10. MAINTENANCE OF PUMP

This solar pump is designed to last years if it is properly cleaned and maintained. If the pump starts losing power or stops working, clean the pump filter and impeller with clean water.



## 11. BATTERY INFORMATION


The Li-ion backup battery pack, like all rechargeable batteries, has a limited life span and becomes less efficient with repeated charge/discharge cycles. As the capacity of the battery reduces over time, you may not achieve the full hours of operation.

If you find that the battery appears less efficient try to "boost charge" it by turning the power off for 1 to 2 sunny days to allow the battery to achieve a maximum charge. Occasional "boost charges" will help prolong the battery life. If after this boost charge your battery still does not perform to expectations, replace it with a new battery.

## 12. BATTERY REPLACEMENT

**IMPORTANT:** Only use original backup battery packs, alternatives may be incompatible which may damage the system and will void the warranty.

See contact information under WARRANTY to order the compatible replacement battery pack.



- Connect the new battery pack connector to the control panel base and insert the battery.
- Replace the panel cover and tighten the screws.

**Dispose of the batteries in accordance with local laws and regulations.**

## 13. TROUBLESHOOTING

Check all solar panel, pump, and LED light connections. Make sure connections are secure and the cables are plugged into the correct ports on the control panel.

Ensure the solar panel is correctly positioned in a full-sun location and is not shaded by trees, shrubs or buildings; refer to page 2.

Check the control panel and confirm it is set to the preferred operation setting; refer to page 3.

If the [Battery Low] light is blinking, the battery pack power is critically low and requires charging. Switch off the pump and leave the solar panel in direct sunlight for at least 6 hours to recharge the battery pack.

Check the water level to make sure the pump is fully submerged.

Check the fountain tubing for kinks and obstructions. Also check to make sure the tubing is tightly connected to the pump.

Check the pump to make sure it is not blocked by or clogged with debris.

The pump may be "air locked" from water levels getting too low or additional water being added. Turn the pump on/off several times to clear any air that may be trapped inside the pump.

## 14. TECHNICAL DATA

MAX. PUMP WATER FLOW: 250LPH

MAX. PUMP WATER LIFT: 90 cm

PUMP WORKING VOLTAGE: DC8.4V~DC6.5V

PUMP WORKING POWER: 1.2W~0.6W

PROTECTION GRADE OF PUMP: IP68

SOLAR PANEL: 2W-9V-0.222A

SOLAR PANEL SIZE: 213 x 202 x 20 mm

PROTECTION GRADE OF PANEL: IP44

LI-ION BATTERY PACK: 7.4V/1.5Ah

PROTECTION GRADE OF BATTERY BOX: IP44

LED LIGHT WORKING VOLTAGE: DC7.4V

LED LIGHT WORKING POWER: 0.15W

PROTECTION GRADE OF LED LIGHT: IP68

## 15. CARE INFORMATION

- Fill the fountain with enough clean water to ensure the pump is fully submerged; never allow the fountain pump to run dry as this will cause damage and invalidate the warranty.
- Clean the fountain and add water on a regular basis.
- Always shut off the power supply before cleaning and maintaining the fountain and the recirculating pump.
- During freezing weather, drain the fountain, disconnect the pump, cables and solar panel, and store indoors; allowing ice to form inside the fountain will damage the fountain and invalidate the warranty.
- The optimal temperature for lithium batteries is 10°C to 45°C, do not use the product beyond this temperature range.

### IMPORTANT!

Make sure the battery has been recharged before storing. Over time, batteries will leak power so if it is stored at no charge, there is a chance it won't accept a charge again. To avoid this problem, turn the pump off and leaving the solar panel out for 1 or 2 sunny days to ensure the battery has been recharged.

## 16. WARRANTY

Thank you for choosing us. We stand behind our brand and the quality of the items we sell. Replacement parts or products will be sent at our discretion within the 1-year warranty period. Proof of purchase, with the date of purchase as well as photos of the merchandise defect, must be provided. Photos are used to determine the cause of defects and for future quality control.

If you have any questions, comments or concerns, feel free to contact us by phone, by email or via our contact us page