





ITEM NO: 1-1456-9

ASSEMBLY INSTRUCTIONS

1. Carefully unpack and identify all parts referring to illustration for parts identification.
2. Turn the power to the installation point OFF.
3. Confirm that the holes on the ring-3 (S) and at the bottom of the bracket (P) align with the mounting hole on the bottom assembly (T). Pass the screws-2 (M) through holes of the ring-3 (S) and bracket (P), and thread into the mounting holes on the bottom assembly (T).
4. Confirm that the holes on the ring-2 (Q) and at the center of the bracket (P) align with the mounting hole on the center assembly (R). Pass the screws-2 (M) through holes of the ring-2 (Q) and bracket (P), and thread into the mounting holes on the center assembly (R).
5. Confirm that the holes on the ring-1 (N) and at the top of the bracket (P) align with the mounting hole on the top assembly (O). Pass the screws-2 (M) through holes of the ring-1 (N) and bracket (P), and thread into the mounting holes on the top assembly (O).
6. Thread the socket assembly (L), the stem (H) and the swivel (A) together as shown. Hand-tighten until snug.
7. Attach the support arms (I) onto the swivel (A), and secure with the screws-1 (G).
8. Confirm that the holes on the support arms (I) align with the holes on the top assembly (O). Pass the mounting screws (K) through holes of the top assembly (O) and the support arms (I), and secure with the finials (J).
9. Unravel the supply power and ground wires and pass them through the stem (H), the swivel (A), the rods (B), the rod (C), the loop (D) and the canopy (E).
10. Thread the bottoms of rods (B) and rod (C) into the stem (H) as shown, and hand-tighten until snug.
11. Thread the loop (D) to the uppermost rod. Hand-tighten until snug.
12. Use carabiner (F) to connect loop (D) to the loop on the canopy (E) and twist the locking mechanism to secure.
13. Refer to the additional installation instructions included with the product for wiring and installation.
14. Install proper bulbs (not included) into each socket referring to the markings and/or labels on the fixture for maximum wattage.
15. Restore power to the installation point and retain this sheet for future reference.