

# LP1520

## Rechargeable Lantern Spotlight



### Features

Rugged-durable design

5W LED

Adjustable, ergonomic handle with locking trigger




Power bank to charge other devices

Rechargeable 4000mAh Li-ion battery (USB cable included)

### Product Warranty

The LP1520 has a Limited 90-Day Warranty Against Manufacturer's Defects from time of purchase.

For warranty claims please contact us by calling 801-553-8886 or sending an email to [info@simpleproducts.com](mailto:info@simpleproducts.com)

ANSI/PLATO FL1 STANDARD			
			
MODES	LUMENS	RUN TIME	BEAM DISTANCE
Flashlight Modes			
High	600 lm	3h	300m
Low	200 lm	6h	200m
Lantern Modes			
High	200 lm	6h	20m
Low	70 lm	10h	10m

### Operation Instructions

#### Flashlight On/Off & Cycle Modes:

Press and release the button on the outside of the handle to turn the light on and off. Press button repeatedly to cycle through flashlight modes (High/Low).



**Lantern On/Off & Cycle Modes:** Press and release the green button on the top of the lantern (opposite of the flashlight lens) to turn the lantern on and off. Press button repeatedly to cycle through lantern modes (High/Low).

**Pivoting Handle:** The LP1520 features a pivoting handle for flexible use of the light. To pivot the handle, push and hold down the button on the side of the handle that says "Push". While keeping this button held down, rotate the handle in either direction until you feel the handle click into the new position.



### Charging Instructions

#### Charging Product:

The LP1520 uses 2 Li-poly; 3.7V 4000mAh rechargeable batteries.

To charge the light, first locate the charge port cover on the top of the lantern (opposite of the flashlight lens).



Lift the cover to expose the charge ports. Plug the small end of the Micro-USB charging cable (included) into the port on the light. Plug the opposite end of the charging cable into a USB power source.

The blue battery indicator lights will light up to indicate the light is charging. The light is fully charged when all 3 battery indicator lights are lit.



The light will turn on and can be used while charging. Rechargeable battery is sealed, and replacement is not necessary.

The LP1520 has a charge time of approximately 8 hours.

#### Charging Other Devices:

The LP1520 can also be used as a power bank to charge other devices.

To use as a power bank, plug the large end of your charging cable into the larger USB port. Plug the opposite end of the cable into your electronic device.

