



CYLIHOSSIS LED DOWNLIGHT SERIES

LED-TB4
LED-TB6

INSTRUCTIONS PERTAINING TO RISK OF FIRE OR INJURY TO PERSONS
READ ALL INSTRUCTIONS

IMPORTANT SAFETY INSTRUCTIONS

SAVE THESE INSTRUCTIONS

TOOLS AND MATERIALS REQUIRED:




Wiring supplies as required by your local Provincial or State Electrical code

SAFETY PRECAUTIONS:

1. TURN OFF ELECTRICAL POWER BEFORE STARTING INSTALLATION OF LIGHT FIXTURE.
2. THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED.
3. CAUTION-RISK OF ELECTRIC SHOCK. CONSULT A QUALIFIED ELECTRICIAN TO ENSURE CORRECT BRANCH CIRCUIT CONDUCTOR.
4. THIS FIXTURE MUST BE INSTALLED WITH COMPATIBLE DIMMER TYPES ONLY. IMPROPER WIRING OF FIXTURE AND/OR USE OF INCORRECT DIMMERS WILL CAUSE CATASTROPHIC FAILURE AND VOID THE WARRANTY.

PART	DESCRIPTION	QTY
A	LED disc light	1
B	Mounting screws	2
C	P3 Wire nut	3
D	P1 Wire nut	2
E	Mounting plate	1



PRIOR TO INSTALLATION, MAKE SURE WHAT DIMMER YOU WILL CONNECT WITH THE FOLLOWING TWO OPTIONS:

OPTION# 1: WITH 0-10V DC LOW VOLTAGE DIMMER

The LED light is compatible to LEVITON # DS710-102 and LUTRON # DVSTV.

<p>Electrical junction box</p>	<p>Gray Purple White Black Ground</p>	<p>Spring Disc light</p>
---------------------------------------	---	------------------------------

1. Prior to installation, install mounting plate into the electrical junction box with mounting screws. Drive screws completely to the end of the junction box.

2. Connect supply wires to wires on fixture with wire nuts. Connect gray to gray, and purple to purple with P1 wire nuts. Connect white to white, black to black, and ground wire to ground wire as grounding connection with P3 wire nuts.

3. Complete the installation by pushing the fixture springs towards the opening in the mounting plate installed on the junction box.

OPTION# 2: WITH TRIAC DIMMER

This LED light is compatible to be dimmed by LEVITON # 6633, LEVITON # 6672, LEVITON # 6631, LEVITON # 6674, LUTRON # DVCL-153P, LUTRON # MACL-153M, LUTRON # CTCL-153P, LUTRON # CTCL-153PD, LUTRON # TGCL-153P. Dimming levels will vary by different dimmer. Dimmer compatible to 120V line volt. 277V is non-dimmable.

<p>Electrical junction box</p>	<p>Ground Black White</p>	<p>P1 Wire nut NC Spring Disc light</p> <p style="font-size: small;">The grey and purple wires are not used. Tighten them with P1 wire nut separately to avoid short-circuit.</p>
---------------------------------------	-----------------------------------	---

1. Prior to installation, install mounting plate into the electrical junction box with mounting screws. Drive screws completely to the end of the junction box.

2. Connect supply wires to wires on fixture with P3 wire nuts. Connect white to white, black to black, and ground wire to ground wire as grounding connection.

3. Complete the installation by pushing the fixture springs towards the opening in the mounting plate installed on the junction box.

! IMPORTANT: Make sure that your dimmable LED Fixture is paired with the correct dimmer type. USE ONLY 0-10V DC LOW VOLTAGE OR TRIAC DIMMERS. REFER TO DIMMER MANUFACTURER'S INSTRUCTIONS FOR PROPER INSTALLATION.

WARNING: Wet-rated lighting fixtures are used in places with direct exposure to water. These locations include almost all outdoor lights, including landscape lighting such as path lights and ground wells. Fixtures rated for wet locations use waterproof seals to protect their internal components from moisture. This does not cover the section where the light is mounted to the junction box. If water is entering through the junction box, it will enter the light fixture, and that is classified as an electrical hazard by most municipal and fire departments.

Customer service: 888-945-5221 Do not return to the store.

Made in China