

# ASSEMBLY AND INSTALLATION INSTRUCTIONS

**WARNING:** TO AVOID RISK OF ELECTRICAL SHOCK, BE SURE TO SHUT OFF POWER BEFORE INSTALLING OR SERVICING THIS FIXTURE.

## Before You Begin:

- Ensure power is turned off at the circuit breaker before installation.
- Read all instructions carefully.
- Installation should be performed by a qualified electrician if you are unfamiliar with wiring.

## Step-by-Step Installation:

1. Press the retractable pin to adjust the suspension cord to the desired height, then release to lock in place.
2. Align the mounting bracket with the junction box and mark drilling locations on the ceiling. Drill appropriately sized holes and insert plastic wall anchors.
3. Secure the mounting bracket to the junction box using the provided screws.
4. Reinforce the bracket installation by tightening the self-tapping screws into the ceiling anchors.
5. Wiring Connections
  - Use wire connectors to connect the fixture's positive wire, negative wire to the corresponding wires from the junction box. Connect the ground wires to the grounding terminal.
  - Ensure no exposed conductors remain outside wire connectors or outside the junction box.
6. Secure the canopy to the mounting bracket using the decorative nuts.
7. Install the bulb into the socket. (Bulb Not Included)
8. Install the glass shade by screwing it onto the socket.

## Safety Instructions:

**To avoid fire, shock, and serious personal injury, follow all instructions carefully.**

1. Do not install or use the light fixture if any part is missing or damaged.
2. To avoid possible electrical shock, be sure electricity is turned off at the main fuse or circuit breaker box before wiring.
3. Make certain no bare wires are exposed outside the wire connectors.
4. All wiring must conform to national and local electrical codes.
5. Follow the recommended instructions for the proper method of wiring your new light fixture. If you feel you do not have enough electrical wiring knowledge or experience, have your light fixture installed by a licensed electrician. Any electrical work not described in this manual should be performed by a licensed electrician.

