



## Installation steps:

**A:** Hook the lower end of the suspension rod (13) onto the metal loop (14) on the fixture, then hook the upper end of the suspension rod (13) onto the top hanging loop (12).

**B:** Tighten the bottom hanging ring of the chain (9) onto the threaded tube (11).

**C:** Thread the ground wire (4) and main wire (7) through the center hole of the chain (9), ceiling canopy (5), and the center hole of the mounting plate (3). Use the chain connector (10) to secure the chain (9) to the hanging loop on the mounting plate (3).

**D:** 1. Connect the positive pole "L" of the main line (7) to the positive pole (+) of the power line using a wire nut (1).

2. Similarly, connect the negative pole "N" of the main line (7) to the negative pole (-) of the power line using a wire nut (1).

3. Use the green screw (2) to secure the ground wire (4) from the fixture and the external ground wire to the mounting bracket (3).

\* Ensure that bare wires are not exposed to prevent electric leakage.

**E:** Raise the ceiling canopy (5) to the ceiling and secure it using the decorative outer ring (8) of the crystal chain (9).

**F:** Attach the glass shade (17) to the lamp holder (18) by tightening the socket ring (16).

**G:** Install the light bulbs (bulbs not included).

## Safety Instructions:

To avoid fire, shock, and serious personal injury, follow all instructions carefully.

1. Do not install or use the light fixture if any part is missing or damaged.
2. To avoid possible electrical shock be sure electricity is turned off at the main fuse or circuit breaker box before wiring.
3. Make certain no bare wires are exposed outside the wire connectors.
4. All wiring must conform to national and local electrical codes.
5. Follow the recommended instructions for the proper method of wiring your new light fixture. If you feel you do not have enough electrical wiring knowledge or experience, have your light fixture installed by a licensed electrician. Any electrical work not described in this manual should be performed by a licensed electrician.