ASSEMBLY AND INSTALLATION INSTRUCTIONS

WARNING: TO AVOID RISK OF ELECTRICAL SHOCK, BE SURE TO SHUT OFF POWER BEFORE INSTALLING OR SERVICING THIS FIXTURE.



Before You Begin:

- Ensure power is turned off at the circuit breaker before installation.
- Read all instructions carefully.
- Installation should be performed by a qualified electrician if you are unfamiliar with wiring.

Step-by-Step Installation:

1.Adjust the chain to the desired length. Thread the main wire and ground wire through the chain and the ceiling canopy.
2.Connect the chain between the hanging ring on the fixture body and ceiling canopy using the quick links.
3.Secure the mounting bracket to the junction box using the provided screws.
4.Wiring Connections
·Note: Use wire connectors to connect the black (L) wire to the black wire, the white (N) wire to the white wire, and the ground wire to the grounding terminal.
·Ensure no exposed conductors remain outside wire connectors or outside the junction box.
5.Secure the ceiling canopy to the mounting bracket using the provided nuts.
6.Place the lamp shade over the socket and adjust to the desired position. Secure the shade by tightening the socket ring. Install the light source (bulb not included) into the socket as indicated.
Restore power and test the fixture for proper operation.

Safety Instructions:

To avoid fire, shock, and serious personal injury, follow all instructions carefully.
1. Do not install or use the light fixture if any part is missing or damaged.
2. To avoid possible electrical shock, be sure electricity is turned off at the main fuse or circuit breaker box before wiring.
3. Make certain no bare wires are exposed outside the wire connectors.
4. All wiring must conform to national and local electrical codes.
5. Follow the recommended instructions for the proper method of wiring your new light fixture. If you feel you do not have enough electrical wiring knowledge or experience, have your light fixture installed by a licensed electrician. Any electrical work not described in this manual should be performed by a licensed electrician.