

SkyLite LED Floor Lamp by Brightech

Before you begin:

1. Inspect lamp before beginning assembly. Some wire connections have been made at the factory and the lamp is ready for assembly.
2. Remove all packing materials from the lamp.
3. To prevent bad connections, avoid pulling wiring connections when removing contents from package or during installation.
4. Lay out all the parts on a flat surface.

Assembly Instructions:

To prevent damage to the pole, please follow the steps below:

1. Take the **LAMP HEAD** and feed the **POWER CORD** through **POLE A**(shortest one without any screw hole).
2. Screw **POLE A** clockwise into the **LAMP HEAD**.
3. Press the **LOCK CONNECTORS** into place and carefully feed the excess **POWER CORD** into **POLE A**.
4. Screw **POLE B**(with dimmer module already assembled in) clockwise into **POLE A**.
5. Feed the **POWER CORD** through **POLE C** and screw **POLE C** clockwise into **POLE B**.
6. Feed the **POWER CORD** through **POLE D** and screw **POLE D** clockwise into **POLE C**.
7. Feed the **POWER CORD** through **POLE E**(with a screw hole) and screw **POLE E** clockwise into **POLE D**.
8. Press the **LOCK CONNECTORS** into place and carefully feed the excess **POWER CORD** into **POLE E**.
9. Line up the screw holes and tighten the provided screw to fix **POLE E** into the **LAMP BASE**.
10. Connect the **DC PLUGS** on the external power cord.
11. Plug **ADAPTER** into outlet and now the lamp is ready for use.

Operating Instructions:

- Press the power spot on the pole and the light brightens to its maximum, then gradually dims to its lowest setting, and back to its highest. When the dimming feature reaches a sweet spot, release the button to hold it there.
- When turned back on, the lamp will go back to its last setting.
- This lamp is suitable for wall switches.

CLEANING AND STORAGE

- Before cleaning make sure the lamp is disconnected from the electrical supply.
- Do not use polishes or cleaners. Wipe clean with a soft cloth or rag. Store the lamp in a dry, clean and stable place.

WARRANTY AND SUPPORT

- Your product comes with a 3-year warranty. Please contact us at www.brightechshop.com or wecare@brightechshop.com

