

# installation instruction

**Step:1** Inner Box Installation Diagram

**Step:1 Assembly complete**      **Step:2 Assembly complete**      **Step:3 Assembly complete**

**Detail of internal frame fittings**

M4\*16 Belt screw Quantity: 8 One      Internal Universal Branch Quantity: 3 One      Internal Branch Quantity: 1 One

Upper frame Quantity: 1 One      Lower frame Quantity: 1 One

**Step description**

- Match the hole no. 1 of the upper inner frame with No. 1 of the inner branch and tighten it with a screw.
- The inner universal branch and the corresponding hole position of the upper inner frame are locked with screws.
- The inner branch No. 2 and the lower box No. 2 corresponding hole position are locked with screws, and then the corresponding other hole positions are locked and fixed with screws.

**Step:2** Frame Installation Diagram

**Step:1 Assembly complete**      **Step:2 Assembly complete**      **Step:3 Assembly complete**      **Step:4 Assembly complete**

**Detail of center frame fittings**

M4\*16 Belt screw Quantity: 8 One      M4\*6 Belt screw Quantity: 2 One      Mid-frame support Quantity: 4 One

Bottom Center frame Quantity: 1 One      Upper Center frame Quantity: 1 One

**Step description**

- The upper middle box No. 1 and the inner box No. 1 hole corresponding to a good use of screw locking.
- The center frame support and the center frame hole corresponding to a good use of screw locking.
- The upper middle box No. 3 no. 4 and the inner box No. 3 No. 4 hole position should be locked with screws, and then the corresponding other hole position should be locked with screws.

**Step:3** Frame Installation Diagram

**Step:1 Assembly complete**      **Step:2 Assembly complete**      **Step:3 Assembly complete**      **Step:4 Assembly complete**

**Detail of frame fittings**

M4\*16 Belt screw Quantity: 8 One      M4\*6 Belt screw Quantity: 5 One

Frame support Quantity: 3 One      Frame 9 Quantity: 1 One      Frame support Quantity: 1 One      Outer upper frame Quantity: 1 One

**Step description**

- The outer upper box No. 5, No. 8 and the Middle Box No. 5, No. 8 hole corresponding to a good use of screw locking.
- Position the No. 9 Branch of the outer frame and the No. 9 Hole of the outer upper frame.
- Apply the screws to the positions of No. 6 and No. 7 of the outer frame and No. 6 and No. 7 of the outer upper frame.
- The Outer Lower Frame and the outer frame supporting the corresponding hole position are locked and fixed.

**Step:4** Installation drawing of the whole lamp

**Step description**

- Fix the hanging plate on the ceiling with expansion screws.
- Connect the client power cord to the lamp power cord and perform insulation treatment.
- Put the lamp holder into the hanging chain and lock it clockwise with the chain lock.
- Insert the ceiling plate into the hanging plate, and lock the hanging plate clockwise with a chain screw, and then lock it clockwise with a chain lock.
- Rotate the lamp pole and fix it on the lamp body, then install it into the lamp plate frame and fix it with screws.
- Put the lamp tube into the lamp cap, and then put the bulb into the lamp cap and lock it clockwise.

**Instructions**

- Please turn off the main power supply before installing the luminaire, do not work with electricity to avoid the risk of electric shock.
- Wear gloves when installing the luminaire to clean the luminaire to prevent rust.
- When installing glass or fragile accessories, please take it lightly.
- Pay attention to the tool, do not scratch the metal plating surface, otherwise it will affect the appearance and rust.
- After the installation is completed, the mode is good. After leaving, turn on the power and start working.

**Precautions**

- Do not install the lamp in a wet place such as a bathroom or outdoors.
- In order to ensure safety, when repairing and inspecting the lamps, please entrust the electrical professional to operate. Non-professional construction is prone to danger.
- When the lamp is abnormal, please cut off the power quickly and ask the professional to check the repair.
- Do not modify or replace the lamp components at will, so as to avoid accidents such as damage, falling, electric shock and fire.

**Accessories details**

① The input line      ② Hanging board kit: 1      ③ Wiring caps: 3      ④ Ceiling plate: 1      ⑤ Hanging chain: 1      ⑥ M4L10 round head screws: 8      ⑦ Light pole: 1      ⑧ Lamp holder: 1      ⑨ Light tube: 6