

# ASSEMBLY AND INSTALLATION INSTRUCTIONS

**WARNING:** TO AVOID RISK OF ELECTRICAL SHOCK, BE SURE TO SHUT OFF POWER BEFORE INSTALLING OR SERVICING THIS FIXTURE.

## Before You Begin:

- Ensure power is turned off at the circuit breaker before installation.
- Read all instructions carefully.
- Installation should be performed by a qualified electrician if you are unfamiliar with wiring.

## Step-by-Step Installation:

1. Press the cord lock (1) to adjust the steel cable (2). Loosen the screw (3) to set the wire (4) to your desired hanging height.
2. Secure the mounting bracket (6) to the junction box using the screws (5).
3. Wiring Connections
  - Use wire connectors (8) to connect the fixture's positive (marked "L") wire, negative (marked "N") wire to the corresponding wires from the junction box.
  - Ensure no exposed conductors remain outside wire connectors or outside the junction box.
  - Secure the ground wires (10) to the grounding terminal using the green screw (9).
4. Place the canopy (12) over the mounting bracket (6), passing the mounting studs (11) through its holes. Secure with the decorative nuts (13).
5. Install the glass shade (14) over the socket (15). Secure it by tightening the retaining ring (16).
6. Install the light bulb (17) into the socket. (Bulb Not Included). Restore power and test operation. Installation Complete.

## Safety Instructions:

**To avoid fire, shock, and serious personal injury, follow all instructions carefully.**

1. Do not install or use the light fixture if any part is missing or damaged.
2. To avoid possible electrical shock, be sure electricity is turned off at the main fuse or circuit breaker box before wiring.
3. Make certain no bare wires are exposed outside the wire connectors.
4. All wiring must conform to national and local electrical codes.
5. Follow the recommended instructions for the proper method of wiring your new light fixture. If you feel you do not have enough electrical wiring knowledge or experience, have your light fixture installed by a licensed electrician. Any electrical work not described in this manual should be performed by a licensed electrician.

