SERA BATHROOM DESIGNS

Model: CHR36LEDMR

36" Chrono LED Mirror

Size: 900*750*35MM



LED Lighted Mirror with Anti-Fog

Installation • Operation • Safety • Warranty

Support:

support@serabathroomdesigns.com

1-833-411-7372

www.serabathroomdesigns.com

5mm copper-free silver mirror

Acrylic back frame and Aluminum frame

LED Mirror with built-in defogger

3000K / 6000K LED light (2 dimming options)

Single-touch sensor switch with dimming function

UL LED driver: 110V

Time & Temperature display function


SERA BATHROOM DESIGNS

36" Chrono LED Mirror

Frosted Edge with Time, Temperature and Defogging

Model: CHR36LEDMR Size: 900*750*35MM

PRODUCT FEATURES



- 36" LED Mirror with built-in defogger
- Acrylic back frame and Aluminium frame
- 5mm copper free silver mirror
- 3000k/6000k LED light
- Single touch sensor switch with dimming function
- UL LED driver : 110V
- Time & Temperature display function

CONTACT US AT:

support@serabathroomdesigns.com

1-833-411-7372

www.serabathroomdesigns.com

SERA BATHROOM DESIGNS

36" Chrono LED Mirror

Frosted Edge with Time, Temperature and Defogging

Size: 900*750*35MM

QUICK START

1. Turn OFF power at the breaker (verify with tester).
2. Locate studs and mark centerline; use included paper template.
3. Install hanging bar/brackets level.
4. Make hard-wired electrical connections.
5. Hang mirror; lock-catch for horizontal mount.
6. Restore power; test touch sensors (light + anti-fog).

SAFETY & COMPLIANCE

- Installation by a licensed electrician only.
- Connect to a GFCI-protected, properly grounded circuit (120 V~ 60 Hz).
- Do not connect to any wall dimmer (ELV/triac). Use a standard ON/OFF switch if desired; dimming happens on the mirror.
- Two-person lift required; use PPE.
- Mount into wall studs whenever possible; use proper anchors for wall type.




GFCI Protected


No wall dimmer


Ground properly


Two-person lift


PPE

CONTACT US AT:

support@serabathroomdesigns.com

1-833-411-7372

www.serabathroomdesigns.com

SERA BATHROOM DESIGNS

36" Chrono LED Mirror

Frosted Edge with Time, Temperature and Defogging

Size: 900*750*35MM

WHAT'S IN THE BOX & TOOLS

INCLUDED



Mirror assembly



Wall screws (x2)



Anchors (x2)

TOOLS NEEDED



Band tap



Level



Pencil



PPE



Drill bits



Electronic drill



Cross screwdriver



Stud finder

CONTACT US AT:

support@serabathroomdesigns.com

1-833-411-7372

www.serabathroomdesigns.com

SERA BATHROOM DESIGNS

36" Chrono LED Mirror

Frosted Edge with Time, Temperature and Defogging

Size: 900*750*35MM

HARDWIRE INSTRUCTIONS


Warning: Manufacturer's warranty shall be void if product is not installed by a licensed professional


Prior to commencing installation, please ensure the following:
- The wall where the product is being installed is able to support the weight of the product
- The main electrical supply has been powered off to complete installation

IMPORTANT: Wiring Instructions for Canada & USA
This fixture's wiring colors may not align with standard North American guidelines. For a safe installation, please re-identify the fixture wires with electrical tape as follows:

LIVE: Wrap black tape on the fixture's White wire. Connect this to your home's Black (Live) wire.
NEUTRAL: Wrap white tape on the fixture's Black wire. Connect this to your home's White (Neutral) wire.
GROUND: Connect the Green wire to your home's Green or Bare Copper ground wire.

Please consult a licensed electrician if you are unsure.





Important
- Hard-wire only. Do not attach a cord-and-plug.
- Use listed wire connectors; make all splices inside approved boxes.
- Do not use a wall dimmer. Use a standard ON/OFF switch if wall control is required.

CONTACT US AT:
support@serabathroomdesigns.com
1-833-411-7372
www.serabathroomdesigns.com


SERA BATHROOM DESIGNS

36" Chrono LED Mirror


Frosted Edge with Time, Temperature and Defogging

Size: 900*750*35MM


WALL MOUNTING INSTRUCTIONS




Measure the distance of the mounting hole.
Drill holes with a suitable sized drill.



Insert the anchor and mounting screw into the wall.



Connect the mirror wires with your main wires and hang the mounting hole to the screw on the wall.



Peel off protective film and clean the mirror with damp cloth.

CONTACT US AT:

support@serabathroomdesigns.com

1-833-411-7372

www.serabathroomdesigns.com


SERA BATHROOM DESIGNS

36" Chrono LED Mirror

Frosted Edge with Time, Temperature and Defogging

Size: 900*750*35MM

OPERATION & FEATURES



MIRROR LIGHT USE


Short touch the Power button (right touch sensor), to turn on / off the mirror light.



DIMMING LIGHT USE

Long touch the Power button (right touch sensor), to dimming the mirror light.

15%, 50%, and 100% dimming levels.



SET UP CLOCK AND TEMP

1. Long touch the Clock button for 5 sec. (left touch sensor), to enter hours setting mode. Sensor starts flashing.
2. Short touch the Clock button (left touch sensor), to set hours.
3. Long touch the Clock button for 5 sec. (left touch sensor), to enter minutes setting mode. Sensor starts flashing.
4. Short touch the Clock button (left touch sensor), to set minutes.
5. Long touch the Clock button for 5 sec. (left touch sensor), to to switch temperature Celsius or Fahrenheit. Sensor starts flashing.

CONTACT US AT:

support@serabathroomdesigns.com

1-833-411-7372

www.serabathroomdesigns.com

SERA BATHROOM DESIGNS

36" Chrono LED Mirror

Frosted Edge with Time, Temperature and Defogging

Size: 900*750*35MM

CARE & CLEANING AND TROUBLESHOOTING

CARE & CLEANING

Wipe with a soft, lint-free cloth; mild non-ammonia cleaner.

Do not use abrasives, pads, acids, or solvents.

Apply cleaner to cloth, not directly on sensor areas.

TROUBLESHOOTING (QUICK FIXES)

No light at install: Confirm breaker ON, correct wiring, internal quick-connects fully seated.

Touch unresponsive: Power cycle at breaker for 60 seconds; clean/dry glass over sensors.

Buzz/Hum: Ensure unit is not on a wall dimmer; verify solid ground.

Anti-fog not warming: Ensure left sensor is ON; feature auto-turns-off after 1 hour.

CONTACT US AT:

support@serabathroomdesigns.com

1-833-411-7372

www.serabathroomdesigns.com