

Thank You for purchasing this Atronics™ timer. We appreciate the trust and confidence you have placed in Atronics™. We are dedicated to the ongoing creation of quality products designed to enhance your living environment. Please visit us at [www.atron.ca](http://www.atron.ca). Thank you for choosing Atronics™!

## PSM118 Heavy Duty 8 Outlet Power Strip with 24-Hour Timer

Heavy Duty 8 Outlet Power Strip With built in 24-Hour Daily Cycle Mechanical Timer  
15-Minute Interval Settings (Each "Tab" or "Tripper" equals 15 minutes)  
Timer Controls 4 Outlets (Timed Outlets)  
Other 4 Outlets are Always Operational (Always-On)  
Grounded Plug  
8 Grounded Outlets:  
4 Grounded Timed Outlets  
4 Grounded Always On Outlets

NOTE: This device is not a surge suppressor and will not afford protection in the event of power surges.

**Caution:** DO NOT EXCEED CAPACITY  
THE COMBINED LOAD SHALL  
NOT EXCEED 15 A OR 1875 W

### Quick Set-Up Overview:

Each "Tab" equals 15 minutes.  
Gently push tabs outward to turn ON for the desired "time ON".  
Leave tabs in the depressed position for the desired "time OFF".  
Rotate dial clockwise to set time. Align current time with arrow.  
Set slide switch to "TIMER" for automatic setting, or to "ON" for always-on setting.

### Programming & Operating Instructions:

1. Set (program) ON and OFF Times:  
Each "Tab" equals 15 minutes. Using fingertip, gently depress tabs to match the desired duration of ON time. Leave the tabs in the raised position for OFF time (period you want power to the plugged-in lamp or appliance OFF). You can have multiple ON and OFF settings for each 24-hour period. NOTE: When setting ON times, make sure the slider switch is set to the "ON" position. Set the slider switch to "TIMER" once you are through programming your setting(s).



### Applications:

Lamp Timer or Appliance Timer  
For Convenience – Come home to an illuminated home  
For Energy Savings – Time your lighting to come ON and OFF as needed  
For Added Safety – Gives your home a lived-in look  
For Indoor Use Only  
Ideal for controlling: Lamps, Seasonal Lighting, Fans, Small Appliances, Window Air Conditioners

### Electrical Ratings:

125 VAC 60Hz  
15 A  
1875 W Resistive  
1000 W Tungsten  
1/3 HP



### Other Specifications:

Programmable Time Increments: 15 Minutes  
Output Control: Timer or Manual Control



2. Set the Time of Day:  
Turn the time dial clockwise until the arrow points to the correct (current) time. The dark tabs are night, and the white tabs are day.
3. Plug-in Lamp or Appliance that is to be Timed (Controlled):  
Plug lamp or appliance into the receptacle on the body of timer. Plug timer into the household outlet.
4. Slider Switch:  
Move the SLIDER SWITCH (located on the side of the timer) to ON to override the timer and provide continuous power to the connected household lamp or appliance. Set to TIMER for timed function. For normal operation, the unit should be set to TIMER.

### SAFETY WARNING:

#### Risk of Electric Shock:

Plug directly into an electrical outlet. Do not use with an extension cord.  
For indoor use only  
Remove (unplug) timer from outlet before cleaning  
Do not use in wet or damp areas  
Keep children away from timer and outlet

#### Risk of Fire:

Do not use to control irons  
Do not use to control cooking appliances  
Do not exceed the electrical ratings

#### Limited Warranty:

Atron Electro Industries Inc. (Atron) warrants to the original purchaser, that this timer (product) shall be free from defects in material and workmanship for a period of five (5) years from the date of purchase. During the "in-warranty" period, defective product will be repaired or replaced at the sole discretion of Atron. This warranty covers normal domestic usage and does not cover damage which has occurred in shipment or failure which results from alteration, accident, misuse, abuse, or improper maintenance.

Defective product should be returned to the original place of purchase within the retailer's stipulated return/exchange period.

If product is found to be defective outside the retailer's return/exchange period, then return product postage/shipping prepaid along with the original purchase receipt to:

Customer Service Department  
Atron Electro Industries Inc.  
429 Alliance Ave.  
Toronto, ON M6N 2J1

Atron will not be liable for incidental or consequential damages.

Additional information may be found at [www.atron.ca](http://www.atron.ca)

Version: JTH v4 Aug 21 2013  
Printed in China

Atronics is a trademark of Atron Electro Industries Inc.  
© Copyright 2013 Atron Electro Industries Inc.