

Decorative String Light Kit

Commercial Grade

- 15 Medium (E26) Base Black Sockets
- 15 pcs Incandescent 25 Watt A19 Nostalgic Loop Medium Base (E26) Bulbs
- Cable/Cord Length = 48 feet
- Socket Spacing = 3 feet



USAGE INSTRUCTIONS

WARNING: When using outdoors - Use portable luminaires. Basic safety precautions should always be followed to reduce the risk of fire, electric shock and personal injury; including the following:

- Use only three-wire outdoor extension cords that have three-prong grounding plugs and grounding receptacles that accept the appliance's plug.
- Ground Fault Circuit Interrupter (GFCI) protection is to be provided on the circuit(s) or outlet(s) to be used for the wet location portable luminaire. Receptacles are available having built-in GFCI protection and are able to be used for this measure of safety.
- Use only with and extension cord for outdoor use, such as an extension cord of cord type SJTW.

INSTALLATION INSTRUCTIONS

IMPORTANT: Turn off the power at the main fuse or circuit breaker box before starting installation.

WARNING: These products may represent a possible shock or fire hazard if improperly installed or attached in any way. Products should be installed in accordance with these instructions; and current electrical code and/or the current National Electric Code (NEC).

CAUTION: To reduce the risk of fire, electric shock or injury to persons:

- Commercial Grade String Lights are intended for installation by trained qualified electrical contractors.
- String Lights are intended for installation by trained qualified electrical contractors.
- Suspend strings properly by attaching suspension cable (not provided) to solid support structures.
- Light sockets must be suspended so that bulbs are facing down ONLY.
- Keep combustible material clear of bulbs. DO NOT allow lamps or sockets to come into contact with walls, ceilings, fabrics associated with shades, blinds or other materials. Lamps should hang freely in a downward direction with a minimum of space from the nearest object.
- DO NOT cluster the bulbs.
- Not intended for installation in ceilings, soffits, cabinets or other enclosed spaces.
- Not intended for lighting aquariums.
- DO NOT secure String Lights to buildings or other structural supports using nails, staples or other sharp conducting materials.
- Avoid damage to the insulation during installation. DO NOT pierce or otherwise compromise wire or socket outer covering, jacket or sheathing.
- Periodically inspect wire and sockets for degradation due to weather. UV light or other damage. Promptly replace worn out light string.
- DO NOT MOUNT THE STRING LIGHTS WITH SOCKETS FACING UPWARD!
- DO NOT OVERLOAD ANY SOCKET MAXIMUM WATTAGE RATING!
- DO NOT OVERLOAD MAXIMUM WATTAGE CAPACITY!
- WARNING-RISK OF ELECTRIC SHOCK!
- DO NOT OVERTIGHTEN BULBS WHEN INSTALLING INTO SOCKETS!

Maximum Wattage per Socket:

# of Light Strings	Maximum Bulb Wattage	# of Bulbs
1	25W	15
2	25W	30
3	25W	45

- Maximum wattage for string run is 1200W. (3 strings x 15 sockets = 1125W)

Incandescent Bulbs
25 Watt
A19 Nostalgic Loop
Medium Base (E26)



To reorder 25W Incandescent A19 Nostalgic Loop Medium Base (E26) bulbs included with this kit ask a store representative or visit to find a distributor. Please reference the item # as shown.