


# ASSEMBLY INSTRUCTIONS



## IMPORTANT

**TURN OFF THE POWER AT THE MAIN FUSE OR CIRCUIT BREAKER BOX BEFORE STARTING INSTALLATION**

**CAREFULLY UNPACK AND IDENTIFY ALL PARTS BEFORE ASSEMBLY. BULBS ARE NOT INCLUDED**

### 1. Wire as per local electrical code.

#### ELECTRICAL CONNECTIONS

1. Cut excess wire ABOVE crossbar to 6 inches. Split the wire into two separate leads. Strip one inch of the plastic insulator from the end of each lead.
2. Connect the half of the wire with the ribbed surface to the white wire of the supply box. Connect the smooth half of the wire (the half with markings) to the black wire of the supply box. Connect the bare copper Ground wire to the green screw of the crossbar (If no crossbar is used connect the Ground wire to the green supply side wire). Use UL listed wire connectors suitable for the size, type and number of conductors. No loose strands or connections should be present. Secure wire connectors with electrical tape.

### 2. Place fixture with post connector onto post and secure with post screw.