




## ASSEMBLY INSTRUCTION



All electrical components must be installed by a licensed electrician in accordance with the National Electric Code and the appropriate local electrical codes.



You will need 5 Medium Base Bulb  
40 Watts recommended 60 Watts Max.  
USE LED BULBS FOR EXTENDED USE

The fixture is Damp rated

### HOW TO INSTALL:

Place the fixture parts on a soft cloth-covered platform before installation of fixture.

1. Screw the Center metal flower stem onto the Center column kit.
2. Place each glass shade over a socket. Secure down with a socket ring and tighten each socket using the socket collar tool.
3. Attach the mounting bar onto the outlet box.
4. Raise the fixture up and do the wire connection. Attach the canopy over the mounting bar and secure with Finial balls.

**WARNING:** This product can expose you to Lead, which is known to the State of California to cause cancer and/or birth defects or reproductive harm. For more information go to [www.p65warnings.ca.gov](http://www.p65warnings.ca.gov)

## ASSEMBLY INSTRUCTION

- A.(2)-Wire connector
- B. (1)-Mounting bar
- C. (2)-Screw
- D. (1)-Canopy (W5"xH1 1/8")
- E. (2)-Finial ball
- F. (1)-Center Column Kit  
Rod ; H2".  
3"Plate with 6 leafs.  
Distributor Box ; Ø3 " ; 10.3mm center hole.  
Side Metal flower stem x5.  
Bottom metal flower stem x5.
- G. (1)-Center metal flower stem with thread finial
- H. (5)-7"Arms
- I. (5)-Metal cover
- J. (5)-Socket cup
- K. (5)-Glass shade ; W5",H3 1/2"
- L. (5)-Socket ring
- M. (1)-Socket collar tool

