

Random Solo,
Design by Chia-Ying Lee

Model Random Solo 18

Random Solo reinterprets the essence of Random in a pendant lamp that expresses a new idea of lightness: the blown glass bubbles break free from the original three-element cluster to float in solitary beauty or combine with each other in delicate lighting solutions.




Random Solo 18	Light source	Diffuser: Blown glass	Cable	Code 2700 K	Code 3000 K
	LED 2700 K 1 W 150 lm 350 mA CRI 90 MacAdam 3-Step	Clear	Clear	17113 0027	17113 0030
	LED 3000 K 1 W 160 lm 350 mA CRI 90 MacAdam 3-Step	Frosted White	Clear	17113 1327	17113 1330
or	LED and driver included	Glossy Smoke	Clear	17113 4327	17113 4330
		Glossy Bronze	Clear	17113 4627	17113 4630
		Pale Gold	Clear	17113 4527	17113 4530
		Mandarin Orange	Clear	17113 5827	17113 5830
		Golden Sage	Clear	17113 7127	17113 7130
		Deep Azure Steel	Clear	17113 8627	17113 8630
		Clear	Black	17123 0027	17123 0030
		Frosted White	Black	17123 1327	17123 1330
		Glossy Smoke	Black	17123 4327	17123 4330
		Pale Gold	Black	17123 4527	17123 4530
		Glossy Bronze	Black	17123 4627	17123 4630
		Mandarin Orange	Black	17123 5827	17123 5830
		Golden Sage	Black	17123 7127	17123 7130
		Deep Azure Steel	Black	17123 8627	17123 8630


Net weight: 0.35 kg Parcels: 2

D

The LED-only light source contained in this fixture must only be replaced by the manufacturer, its support service or similarly qualified personnel.



The LED driver contained in this fixture must only be replaced by the manufacturer, its support service or similarly qualified personnel.



info@lodes.com
lodes.com

LODES

Random Solo 18

LED
2700 K
1 W
150 lm
350 mA
CRI 90
MacAdam 3-Step

Photometric data

