

Open the package and first sort out the accessories according to the list of accessories

Accessory List



A Base plate * 1



B layer of boards * 2



C Long pillars (with three holes) * 1



D Long pillars (without holes) * 3



E Hooks * 9



F Long pillars (with one hole) * 3



G Medium-long pillars (with two holes) * 1



H Short pillars (with one hole) * 1



Step 1: Tighten the unthreaded long pillar D against the hole position on the base plate A.



Step 2: Install the layer board B onto the unthreaded long pillar D.



Step 3: Install the long pillar F onto the layer board.



Step 4: Installation of single-hole long column is completed.



Step 5: Install layer board B onto single-hole long column F.



Step 6: Install three-hole long column C, two-hole medium-long column G, single hole short column H onto layer board B.



Step 7: The three top supports have been installed.



Step 8: Insert the hook E into the corresponding holes on the pillar.



Step 9: Installation is complete.

Installation Diagram