#### DESCRIPTION

The H27ICAT housing is designed for use in shallow ceilings where  $2" \times 6"$  joist construction is used. The wide variety of trims available allows a number of different lighting effects to be created with one basic housing.

#### **APPLICATION**

The H27ICAT is designed for shallow ceilings where insulation is present. The H27ICAT housing is of AIR-TITE construction and prevents airflow between living spaces and unconditioned attic areas.

# Catalog # Type Project Comments Prepared by Date

#### **DESIGN FEATURES**

#### A...Housing

Aluminum housing for greater heat dissipation.

#### B...Socket Plate

Adjustable socket plate for different lamps types and sizes.

#### C...Plaster Frame

Housing adjusts in plaster frame 1 3/8" to accommodate different ceiling thicknesses.

#### D...Junction Box

Junction box features include:

- UL listed for through branch circuit wiring
- Positioned to accommodate straight conduit runs
- Seven 1/2" trade size conduit knockouts with true pry-out slots
- Slide-N-Side™ connectors allow non-metallic sheathed cable to be installed without tools and without removing knockouts. Accepts a wider range of non-metallic sheathed cable – the standard cable types used in lighting for both U.S. and Canada.
  - Allows wiring connections to be made outside the junction box

- Simply insert the cable directly into the trap after connections are made
- accommodates the following standard non-metallic sheathed cable types: (US) #14/2, #14/3, #12/2, #12/3 (Canada) #14/2, #14/3, #12/2

## E…GOT NAIL! Pass-N-Thru™ Bar Hangers

Bar Hanger Features include:

- Pre-installed nail easily installs in regular lumber, engineered lumber and laminated beams
- Safety and guidance system prevents snagging, ensures smooth straight nail penetration and allows bar hangers to be easily removed if necessary.
- Automatic levelling flange aligns the housing and lets you hold the housing in place with one hand while driving nails
- Housing can be positioned at any point within 24" joist span
- Score lines allow "tooless" shortening for 12" joists
  Bar hangers may be
- repositioned 90°
- Bar hangers do not need to be removed from frame for

shortening

 Integral T-bar clips snaps onto T-bars - no additional clips required

#### F...Socket

Porcelain socket with nickel plated brass screw shell.

#### G...Thermal Protector

Integral Thermal Protector deactivates fixture if an incorrect lamp is used or if ceiling insulation material is not applied correctly.

#### Labels

- UL Listed for Damp Location
- UL listed for Feed Through
- UL listed for Direct Contact with Insulation and combustible material
- CSA Certified

Meets following requirements:

- State of California Title 24
- Washington State Energy Code
- International Energy Conservation Code (IECC)
- New York State Energy Conservation Construction Code
- Certified Under ASTM-E283



# **H27ICAT**

6" Insulated Ceiling AIR-TITE Recessed Housing

6" TRIMS

FOR USE IN INSULATED CEILINGS

FOR USE IN SHALLOW CEILINGS




with all trims listed





# **UPGRADE FEATURES:**

- SLIDE-N-SIDE III™ JUNCTION BOX
- GOT NAIL!™ BAR HANGERS
- PASS-N-THRU™ BAR HANGERS • REGRESSED LOCKING SCREW
- HALO ID ON PLASTER FRAME



7 1/2" [191mm] 10 1/2" [267mm]

Top View

Ordering Information on reverse.

ADV051278 Supersedes ADV042498 ADV023112 & ADV000307) 8/05

TAB: Recessed Incandescent

#### ORDERING INFORMATION

#### SAMPLE NUMBER: H27ICAT-426RG

Order housing, trim and accessories separately.

Housing

H27ICAT=6" Insulated Ceiling AIR-TITE Shallow Housing

#### Trims

#### REFLECTORS

426

# Specular Reflector Cone 75W PAR30, 65W BR30, 65W PAR30L, 50W PAR30

426=White Trim Ring, Specular Clear 426H=White Trim Ring, Haze Reflector 426RG=White Trim Ring, Residential Gold Reflector

426CG=White Trim Ring, Champagne Gold Reflector 426MB=White Trim Ring, Specular Black reflector

426SN=Satin Nickel Trim Ring and Satin Nickel Reflector 7 1/4" (184mm) OD:

#### **BAFFLES**

# Baffle

310

65W BR30, 75W PAR30L, 50W PAR30 310P=White Trim Ring, Black Baffle 310W=White Trim Ring, White Baffle 310SN=Satin Nickel Trim Ring, Black Baffle

OD: 7 1/4" (184mm)

Baffle 65W BR30, 50W PAR30

312P=Black Baffle 312W=White Baffle OD: 7 1/4" (184mm)



312

Metal Baffle 50W PAR30, 65W BR30, 75W PAR30L, 310SN=Satin Nickel Trim Ring, Black

Baffle 7 1/4" (184mm) OD:

# **ADJUSTABLES**

Eveball 50W R20, 50W PAR20 77P=White Eyeball OD: 8" (203mm)



75W R30, 75W PAR30L 78P=White Eyeball 78SL=Silver Éyeball 78B=Brass Eyeball 78PB=Polished Brass Eyeball 78PAT=Polished Brass Eyeball 78SN=Satin Nickel Brass Eyeball OD: 8" (203mm)



Double Bubble - 60° Tilt 150W PAR38

90P=White Double Bubble Adjustable 8" (203mm)

Coilex Regressed Eyeball 50W PAR30, 50W PAR30L, 60W BR30 420P=Black Baffle, White Eyeball 420PB=Black Baffle, Polished Brass Eyeball 420W=White Baffle, White Eyeball OD: 7 1/4" (184mm)

## OPEN

Open 65W BR30, 75W PAR30 300P=White Open 300SN=Satin Nickel Open OD: 7 1/4" (184mm)



328

420

65W BR30, 75W PAR30L, 50W PAR30 328P=White Splay OD: 7 3/4" (197mm)

White Splay Trim

**Drop Opal with Reflector Cone** 

#### LENS



40W A19 171P=Drop Opal 171PS=Drop Opal Shower Light 7 1/4" (184mm)

172

Shower Light 60W A19, 50W PAR30 172PS=White Trim Ring 172SN=Satin Nickel Trim Ring OD: 7 3/4" (197mm)

#### Accessories

Metal Trim Rings Compatible with 310, 312, 420, 426 TRM6P=White Metal TRM6PB=Polished Brass TRM6C=Chrome TRM6MB=Black Metal TRM6SL=Silver Metal TRP7MB=Black Plastic TRP6SN=Satin nickel

## Oversize Trim Rings

For use when ceiling opening is cut too large. Compatible with 310, 312, 420, 426 OT400P=9 1/4" White Metal OT403P= 8" White Plastic

# Step Down Transformer

Steps 277V line voltage down to 120V fixture operating voltage. 150VA max. H277=150VA Max.

