



## Emergency Exit Light by Wen Lighting



The LED exit sign light by LEDMyplace is known for its design and versatility. This Green LED Exit Sign consumes 4W and solves almost any mounting configuration problem. The lighting fixture comes with an emergency light. This fixture is constructed of high-grade acrylic with customizable directional arrows to point towards exit direction. The removable front cover makes installation and maintenance headache-free!

## Features

- Available Wattage: 4W
- Output: 1W max
- Color: Red
- 1.2V Nickel Cadmium Battery
- Voltage: AC120-277V
- Charging time: 24 hours
- Discharge time: 90 minutes
- Working Temp: 32°F to 140°F
- Dimension: 11.71x7.26x1.75 In
- UL Certificate.
- Warranty: 2 Years

MPN	Wen Code	Wattage	Voltage	Fixture Color
EX004	WEN-7037R	4	AC100-277V	Red
EX005	WEN-7037G	4	AC100-277V	Green



## WARNINGS AND CAUTIONS

- Turns power off before inspection, installation or removal. Risk of electric shock do not use where directly exposed to water or weather.
- Suitable for damp locations.
- This device is not intended for use with emergency exit fixtures or emergency exit lights.



+1-502 303 4518

+1-270 422 2524

info@wenlighting.com

www.wenlighting.com