

Project:

Fixture Type:

Location:

Contact:

LED Flush Mount • Damp Location



Specifications:

Description:

This collection features a 120V alternating current (AC) source which eliminates the need for a traditional LED driver.

Construction:

- Etched ribbed glass bowl -8-7/16" dia.
- Plated Brushed Nickel, painted Antique Bronze and White
- Steel construction
- LED Module is replaceable
- Flicker-free dimming to 10% brightness with most ELV type dimmers (See Dimming Notes)
- Covers a standard 4" recessed outlet box
- Mounting strap for outlet box included

Performance:


| | |
|---------------------|---|
| Number of Modules | 1 |
| Input Power | 17W |
| Input Voltage | 120V |
| Input Frequency | 60Hz |
| Lumens | 1211 (LM-79) |
| CCT | 3000K |
| CRI | 90 |
| LPW | 71 |
| Life | 60,000 (L70/TM-21) |
| EMI/RFI | FCC Title 47, Part 15, Class B |
| Min. Start Temp | -30° C |
| Max. Operating Temp | 30° C |
| Warranty | 5 yrs. |
| Labels | cCSAus certified for damp locations ENERGY STAR® qualified |

Images:



Dimensions:

| | |
|---------|--------|
| A | B |
| 11-3/8" | 5-3/4" |



Catalog number:

| Finish | Color Temp | CRI |
|------------------|------------|----------|
| - Brushed Nickel | - 3000K | - 90 CRI |
| - Antique Bronze | | |
| - White | | |



Dimming Notes:

This collection is designed to be compatible with many Electronic Low Voltage (ELV-Reverse Phase) controls. The following is a partial list of known compatible dimmer controls:

Electronic Low Voltage ELV Reverse Phase Controls

| | | |
|---------|---------------|-------------------------|
| Lutron | Diva Series | (Part Number DVELV-300) |
| Lutron | Nova T Series | (Part Number NTELV-300) |
| Lutron | Vierti Series | (Part Number VTELV-600) |
| Lutron | | (Part Number MAELV-600) |
| Lutron | | (Part Number SPELV-600) |
| Leviton | | (Part Number AWRMG-EAW) |
| Leviton | | (Part Number 6615-P) |

Digital type dimmers are not recommended.

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.