

KOS SQUARE 140 LED

astro

GENERAL

LOCATION:	Bathroom/Interior/Exterior
CLASS:	cULus (Class 1)
LOCATION RATING:	Wet
DRIVER REQUIRED:	Mains 120V
INSTALLATION ORIENTATION:	Ceiling Mount
FITTING METHOD:	4" Octagon Box
MAIN MATERIAL:	Metal - Aluminum
DIMENSIONS (mm):	H: 142 W: 115 D:115
DIMENSIONS (inch):	H: 5.59 W: 4.53 D:4.53
CUT OUT HOLE (mm/inch):	-
RECESS DEPTH (mm/inch):	-
FIRE RATING:	-
CABLE LENGTH (mm/inch):	-
GROSS WEIGHT (lb):	3.52
ADA COMPLIANT:	Yes - if installed in compliance with ADA 307.4
IC RATING:	-

LAMP

LIGHT SOURCE:	AC LED Module
WATTAGE:	11.8W
LAMP INCLUDED:	Yes (Integral)
MAXIMUM LAMP LENGTH (mm/inch):	-
LUMINOUS FLUX (lm):	950
COLOUR TEMP (K):	3000
CRI (Ra):	90
MACADAM ELLIPSE:	3-Step
TILT ADJUSTABLE ANGLE (°):	-
ROTATION ADJUSTABLE ANGLE (°):	-
LIFETIME (hrs):	L70 >40000
BEAM ANGLE (°):	36

ELECTRICAL

SWITCHED:	No
DIMMABLE:	Yes
DIMMING METHOD:	Phase - Leading & Trailing Edge
SUPPLY FREQUENCY (Hz):	50/60
DRIVER/BALLAST VOLTAGE (V):	110-130
DRIVER LIFETIME (hrs):	40000
EFFICACY (lm/W):	80

ADDITIONAL INFORMATION:


SHADE INCLUDED:	-
SHADE/DIFFUSER MATERIAL:	Glass
SHADE/DIFFUSER FINISH	Clear
F MARK:	Suitable for mounting on flammable materials



CODE: 1326054
FINISH: TEXTURED WHITE



CODE: 1326056
FINISH: TEXTURED BLACK



CODE: 1326057
FINISH: TEXTURED GREY

TO MAINTAIN THIS PRODUCT TO ITS BEST CONDITION, PLEASE VIEW OUR CARE AND CLEANING GUIDE ON THE SUPPORT SECTION OF THE ASTRO WEBSITE.

Pour entretenir au mieux ce produit, veuillez consulter notre guide d'entretien et de nettoyage, dans la rubrique d'aide sur le site Web d'Astro.

Um dieses Produkt im besten Zustand zu erhalten, beachten Sie bitte unseren Leitfaden zu Pflege und Reinigung im Abschnitt „Support“ auf der Astro-Website.

Per mantenere questo prodotto nelle sue migliori condizioni, consultare la nostra guida per la manutenzione e la pulizia nella sezione dedicata all'assistenza del sito Web Astro.

PRODUCT ELEVATIONS

astro

Please note that some dimensions may vary slightly due to manufacturing tolerances, this includes cable entry and fixing holes.

