

Aeon CineWhite® A8K Dimensions Table - M Type

Model Number	Nominal Diagonal	Screen Material	Gain	Overall Width (A)	View Width (A1)	Overall Height (B)	View Height (B1)	Frame Width (C)	Frame Thickness (D)	Center Support Bar Length (E)	Acoustic Area Width (F)	Acoustic Area Height (F1)	Packing Dims (LxWxH)			N.W.	G.W.
Unit: Inch																lbs	lbs
AR103H-A8K	103"(16:9)	CineWhite® A8K	1.1	90.2	89.2	51.1	50.2	0.4	1.3	46.5	85.4	46.4	59.3	11.0	7.9	21.4	28.4
AR123H-A8K	123"(16:9)	CineWhite® A8K	1.1	107.6	106.6	60.9	60.0	0.4	1.3	56.3	102.8	56.2	68.9	11.0	7.9	26.2	33.9
AR135H-A8K	135"(16:9)	CineWhite® A8K	1.1	118.6	117.6	67.1	66.1	0.4	1.3	62.4	113.8	62.3	82.7	11.0	7.9	29.7	38.1
AR150H-A8K	150"(16:9)	CineWhite® A8K	1.1	131.7	130.7	74.5	73.5	0.4	1.3	69.8	126.9	69.7	82.7	11.0	7.9	32.3	43.2
AR138C-A8K	138"(2.35:1)	CineWhite® A8K	1.1	128.0	127.2	54.9	54.1	0.4	1.3	50.4	123.3	50.3	68.9	11.0	7.9	25.7	35.9
AR158C-A8K	158"(2.35:1)	CineWhite® A8K	1.1	146.4	145.6	62.8	62.0	0.4	1.3	58.3	141.8	58.2	82.7	11.0	7.9	31.7	42.5
Unit: mm																kgs	kgs
AR103H-A8K	103"(16:9)	CineWhite® A8K	1.1	2290	2266	1299	1275	9	34	1181	2169	1178	1505	280	200	9.7	12.9
AR123H-A8K	123"(16:9)	CineWhite® A8K	1.1	2732	2708	1548	1524	9	34	1430	2611	1427	1750	280	200	11.9	15.4
AR135H-A8K	135"(16:9)	CineWhite® A8K	1.1	3012	2988	1704	1680	9	34	1586	2891	1583	2100	280	200	13.5	17.3
AR150H-A8K	150"(16:9)	CineWhite® A8K	1.1	3344	3320	1892	1868	9	34	1774	3223	1771	2100	280	200	14.7	19.6
AR138C-A8K	138"(2.35:1)	CineWhite® A8K	1.1	3250	3230	1395	1375	9	34	1280	3133	1278	1750	280	200	11.7	16.3
AR158C-A8K	158"(2.35:1)	CineWhite® A8K	1.1	3718	3698	1595	1575	9	34	1480	3601	1478	2100	280	200	14.4	19.3

Note: Data error may be ±1"

The listed measurements are for general reference only. Please contact Elite Screens to verify product design and dimensions before attempting to integrate its products with any structural or furniture modification. Although a manufacturer may offer product advice, it may be taken or disregarded at the integrator's discretion. Elite Screens will not be held responsible or be otherwise liable for faulty installations.

