After opening the package, first classify the accessories according to the accessories table, and then start installation after classification.

Installation diagram

1

Install drawer with screw B. handle

Just insert it directly into the panel to break and bend

2

Fix handle 19 on door 7 with screw D

Use screw C mounting iron sheet, then put iron pin 15

Inserted at both ends of the door

3



Fix handle 19 on door 6 with screw D

Use screw C mounting iron sheet, then put iron pin 15

Inserted at both ends of the door, there are 3 doors

4



On Laminate 3 and door laminate 5 and panel 10

Fix door stopper 17 with screw C

They have two small holes on their faces

5

Drawer bar is a little bulging

Fix door stopper 17 with screw C

On partition 9

6



Use screws A to handle Bracket 1 and Bracket 2 fixed on base plate 4

Slot of bracket and slot of base plate 4

To be put together

Base Plate 4 this hole

Must be left and up

7



Fixed on base plate 4

Note: door stopper

Use screw A to handle partition 9

Distance from top

Small up

8



Insert backplane 8

9



Install with screws A

Laminate 5: only weekly

There is a hole in the corner of laminate 5

Must be left and down

10



The iron pin of door 7 is inserted in

Baseboard and laminate 5

Then screw A to handle the laminate 5

Screw on other screws

11



Fix Door 6 with screw A

Insert backboard 8,

12



Fix laminate 3 with screws A

13



Insert backboard 8,

Fix Door 6 with screw A

14



Fix laminate 3 with screws A

15



Fix Door 6 with screw A

Insert backplane 8

16

Fix panel 10 with screws A

17

Note: Installation of Layer 3/4/5/6

The way is the same, just accessories

The quantity will be different

Installation completed