

LED DEFOGGING MIRROR

Production safety instruction

- This product need to unplugged from electrical outlet before cleaning or any other servicing,;
- Always keep supervision when it is used by or near to Children, invalids or disabled persons;
- Never open this product if it has any damage or not working properly;
- Do not use outdoors;
- Do not put any object into any opening of the product;
- Turn all controls to off position before remove plug;
- Clean glass with damp cloth and wipe dry. Do not use harsh or abrasive cleaning solvents;
- This product is for use on a nominal 120-volt circuit and has a grounding plug. Make sure that the product is connected to an outlet having the same configuration as the plug. No adapter should be used with this product;
- For a grounded, cord-connected product rated max 15 amperes and intended for use on a normal 120-volt supply circuit.

TOOLS & HARDWARE REQUIRED

- Pencil
- Tape Measure
- Level
- Drill
- Screwdriver
- Wall Anchors (2)
- Screws (2)

INSTALLATION

Consult a qualified professional if you are unsure about the wall type, whether utility lines are behind the wall, or if unsure about what mounting hardware to use.

- Measure the distance between the two brackets on the back of the mirror.
- Use level and mark the same distance on the wall at the height where the mirror will hang.
- Drill a hole at each mark, then install wall anchors and screws. Leave a small gap between the wall and the screw to allow space for the bracket to rest.
- Align brackets and hang mirror on screws.
- Plug cord into a standard 120v wall outlet.

OPERATION

- **BUTTON LIGHTS:** Blue – Standby | White – On | No Light – Off
- **LIGHT:** From standby, short press power button to turn ON. When on, short press power button until light turns off to STANDBY.
 - **COLOR TEMPERATURE:** Short press power button to cycle through color temperatures -- 6000K White • 4000K Natural • 3000K Warm.
 - **BRIGHTNESS:** Long press power button to adjust brightness.
- **DEFOG:** From standby, short press defog button to turn ON. When on, short press defog button to turn off to STANDBY .