

SECURE LINK™ (Supports Matter)

PGH260

Link to Matter. Connect and control Lockly smart locks together with other smart home devices via Matter controller*.

Connect to Wi-Fi. For live monitoring, control and status, monitor open/closed door status¹ with real-time alerts sent to your smartphone, no matter where you are.

Grant access, even when you're not home. Lock and unlock door from anywhere.

Hands-free voice control. Control and check your door status using your voice through Siri, Alexa and Hey Google**.

Plug & Pair. Easy to set up, just plug and pair. Provides communication reliability, stability, security and better connectivity.

COMPATIBLE DEVICES

Models Supported Matter*	PGD228FN/SL/SW, PGD238LM/LE, PGD628FA, PGD628WA, PGD679D/L/DZ/LZ, PGD678, PGD688, PGD6SA, PGD7A, PGD7AW, PGD7SA, PGD7Y, PGD7YW, PGD728FA, PGD728WA, PGD829#
Optional Add-On	PGA383 Wireless door sensor & sensor magnet ¹ required for door status (open/closed) monitoring

SPECIFICATIONS

Product Dimensions	2 3/4" x 2" x 5/8" (70 x 50 x 16.5 mm), US power supply adapter included
Color	White
Power Supply	100-240V-50/60Hz AC input, 5V/1A output
Visual and Audible	LED (Red, Green), single settings button
Communication Standards	Matter Protocol, BLE 4.2, Wi-Fi 2.4GHz, bi-directional RF433.92MHz and AES 256 Encryption, Lockly 2.0 proprietary encryption
Communication Range (networked solution)	Up to 98' (30m) BLE, Up to 197' (60m) Wi-Fi, Up to 164' (50m) RF433.92MHz, Unobstructed open environment
Command Response	Responds to command from host in less than 3 seconds
Connectivity Options	Lockly Home app, Lockly Manager app, LocklyOS. ALL in real-time communication
Available Signal Status	Battery Status via App, Open/Close Door Status, Bluetooth Connectivity Indicator, Sensor LED (Red/Green)
Operating Temperature	-14°F to 140°F (-10°C to 60°C)
Material	ABS Plastic
Compliance	RoHS, FCC



 **matter**

Important: Make sure to update the firmware of your Lockly Smart Lock to the latest version via OTA (Over-The-Air) before pairing it with the Secure Link. Please note that only 24GHz Wi-Fi is supported. Make sure your network is set up accordingly to avoid issues with 5GHz Wi-Fi.

* Check the Lock Serial on the Activation Card for an "N" to ensure compatibility with our Matter Link. If the Lock Serial does not contain "N" the lock will be incompatible.

Check the Lock Serial on the Activation Card for "FN1", "FN2" or "FN3" to ensure compatibility with our Matter Link. If the Lock Serial does not contain any of these three sets of digits, the lock will be incompatible.

** Hey Google, Siri, Alexa and Smartthings are connected via Matter.

¹ Contact customer support to purchase.

WIRELESS DOOR SENSOR

PGA383

Lockly Guard Wireless Door Sensor is simple and very easy to install. It only uses AAA battery for long and optimal operation. Door Sensor can provide the ability to verify that your door is securely closed and not ajar. It also sends push notifications to your phone or confirms via voice assistants when the door unlocked or locked.

Lockly door sensor is based on bidirectional RF433.92MHz and Lockly 2.0 proprietary encryption, providing communication reliability, stability for better security.

An ideal companion to Lockly Matter Link or as replacement for wired door sensors if your door structure is not suitable for such.

COMPATIBLE DEVICES

Network Hub	Secure Link (PGH260)
-------------	----------------------

SPECIFICATIONS

Product Dimensions	Door Sensor: 2 3/4" x 1/2" (75 x 20mm), Sensor Magnet: 2 3/16" x 3/8" (55 x 10mm)
Color	White
Power Supply	AAA battery (included)
Visual and Audible	LED (Red, Blue)
Communication Standards	RF433.92MHz
Communication Range (networked solution)	Up to 164' (50m) RF433.92MHz, Unobstructed open environment
Connectivity Options	Lockly Home app, Lockly Manager app, LocklyOS. Matter, ALL in real-time communication
Credential Technologies	Bidirectional RF433.92MHz, Lockly 2.0 proprietary encryption
Operating Temperature	-4°F to 151°F (-20°C to 66°C)
Operating Humidity	0 to 95% RH
Material	ABS Plastic
Compliance	RoHS, FCC

