

4.DMX console address setting

Address	1	2	3	4	5	6	7	8	9	
Address DATA	1	2	4	8	16	32	64	128	256	Series connecti on address
Address ON/OFF	ON	OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF	1
	OFF	ON	OFF	OFF	OFF	OFF	OFF	OFF	OFF	2
	OFF	ON	OFF	ON	OFF	OFF	OFF	OFF	OFF	10
	ON	ON	OFF	OFF	OFF	ON	ON	OFF	OFF	99
	OFF	ON	OFF	OFF	OFF	OFF	OFF	OFF	ON	258
	ON	ON	ON	ON	ON	ON	ON	ON	ON	512

86 RGB LED STATE LIGHT



Please carefully read the instructions before use.