

4 ways to unlock

with mechanical override **DDL210X-1H**

Featuring a variety of access methods, you can unlock this lock by fingerprint, PIN code, one-time PIN code or a key. Besides, auto-lock, ultra-long battery life and multiple alarm functions provide you additional peace of mind.











Matte black














4 ways to unlock



Choose the method convenient for you



Multiple alert function



Simple sharing

Share one-time PIN code anytime, anywhere



Biometric identification A faster & easier digital life



Ultra-long battery life

Lasts up to 1 year*



Modern design Modernize your door



Voice guide

To assist with setting up your lock



Easy installation

With just a screwdriver



Specifications

Key Features		Modes		Overview	
ANSI/BHMA grade 2	Safety	Manual mode	Operation mode	Aluminum alloy	Material
AES128		Auto mode		Satin nickel / Matte black	Color
Local storage		Away mode	Security mode	Dead bolt	Bolt type
Low battery alarm	Alarms	Privacy mode		SC1	Keyway
Wrong entry limit alarm			Power	N/A	Connectivity
Jam alarm		4 AA batteries	Power supply		Unlock Methods
Generate one-time PIN codes ONLY	Remote control (12 months*	Battery life	Fingerprint	Unlocking from outside
English / French / Spanish	Language	g Not supported	Emergency powerin	PIN code	
igation Real person voice navigation	Voice navigation	nent	Operating Environr	One-time PIN code	
		From -35℃ to 66℃	Temperature	Key	
		0-95%	Humidity	Thumb turn	Unlocking from inside
		ments	Installation Require		Max Credentials Capacity
		1-3/8 to 2 inch (35-50mm)	Door thickness	50	Fingerprint
		Left inside / Left outside	Opening direction	1	Master PIN code
		Right inside / Right outside		20	User PIN code
		1-1/2 or 2-1/8 inch (38/54mm)	Cross bore hole	Unlimited	One-time PIN code
		3/8 or 2-3/4 inch (60mm/70mm)	Backset 2-		

^{*1} year/12 months: This refers to the average time determined by an internal test lab. It is based on the use of PIN code unlocking 8 times, 8 times auto locking, 4 times manual unlocking, 4 times manual locking per day. Actual time may vary due to different usage frequency.