



## PREPARATION before INSTALLATION:

1. If an existing fixture is being replaced, remove it and note to which wire in the outlet box the original fixture was attached.
2. Before discarding the carton, double-check the packaging to make sure all parts have been found.
3. This fixture was designed to be mounted on an octagon outlet box. The box must be securely mounted to the structure of the building.

## IMPORTANT:

1. **WARNING** - Disconnect power before relamping or wiring the fixture. Turn off the entire electrical circuit to which the lighting fixture is attached.
2. Installation and maintenance of this fixture should be completed by a licensed electrician.
3. Failure to install the fixture correctly could result in serious injury or death.
4. Read all instructions before starting installation.

## INSTALLATION STEPS:

Before installation, please turn off the power supply.

- A. Secure the mounting bracket (2) to the junction box using screws (3).
- B. Use wire connectors (1) to connect the black wire to the household hot wire, and the white wire to the household neutral wire.

Use the green grounding screw (5) to connect the ground wire (6) and the household ground wire to the mounting bracket (2).

(Note: Ensure that no bare wires are exposed to prevent electrical shock. )

- C. Fix the ceiling plate (9) to the mounting bracket (2) using the waterproof gasket (8) and nut (7).